




**Haylou-GT2**  
TWS BT Earphones  
User Manual

**Overview**



**What's in the Box**

Eartips \* 3 pairs (medium size eartips have been put on), earbuds, charging case, charging cable, user manual.

**Basic Parameters(earbuds)**

Operation range: 10m (open space with no obstacle)  
Battery capacity: 43mAh (single earbud)  
Charging time: approx. 2hr  
Talk time: approx. 3.5hr  
Standby time: approx. 150hr  
Input parameter: 5V  $\pm$ 50mA  
Battery type: li-ion  
Bluetooth version: v5.0

**Basic Parameters(charging case)**

Input parameter: 5V  $\pm$ 50mA  
Output parameter: 5V  $\pm$ 50mA  
Charging time: approx. 2hr  
Standby time: approx. 4 months  
Battery capacity: 380mAh  
Battery type: li-ion


**How to Wear**



Please adjust Mic towards your mouth to gain better calling experience.


**How to Charge**

For first time use, please remove stickers from the case then top up earbuds.




**Power-on**

Pick up earbuds from the case to power them on. If earbuds are out of the case, hold MFB for 1.5s to power them on (LED glows white for 1s).



**Power-off**


Pop earbuds into the case to power them off. Hold MFB for 4.5s to power them off. (LED glows red for 2s).



**Stereo Mode**

Auto connection: take up two earbuds from the case, they will auto power on and pair with each other in 3s. When LED on right earbud blinks white slowly, search for Haylou-GT2\_R and tap on cellphone to connect both earbuds to cellphone.

If earbuds fail to connect to cellphone, please pop them back into case and repeat the above steps. Earbuds will auto reconnect to the last device in connectivity records, if any. (Bluetooth faculty needs to be activated).  
Note: GT2 has been set to factory before shipping out.



Manual pairing: power off earbuds then manually power on them. Earbuds will auto pair with each other when LED on right earbud blinks white slowly. On cellphone, search for GT2\_R and tap to connect both earbuds to cellphone.


**Mono Mode**

Auto Connection: take up either earbud from the case. The earbud will auto power on and LED will then blink white slowly. On cellphone, search for Haylou-GT2\_R/L and tap to connect the earbud to cellphone.


Earbud will auto reconnect to the last device in connectivity records, if any. (Bluetooth faculty needs to be activated).  
Note: it will cost more time for left earbud to reconnect to cellphone.  
Manual pairing: power off earbuds then manually power on either earbud. When LED on the earbud blinks white slowly, search for Haylou-GT2\_R/L and tap on cellphone to connect.

**Charge the Case**

Charge the case via USB cable. LED will glow solid red when charging and turn off once topping up.



**Functions**



- Double press MFB on left earbud  
Skip track backward
- Double press MFB on right earbud  
Skip track forward
- Press MFB  
Pause music/resume playing
- Press MFB  
Answer incoming call/end the call
- Hold MFB for 1.5s  
Ignore incoming call
- Triple press MFB  
Activate voice assistant (standby)

**Daily maintenance**

Please do not shower with earbuds. Do not wear them in rainy day. Do not leave them in washing machine or other extreme situations. Clean them with dry cloth after use in pursuing a longer service life.

**Caveats**

1. Please charge the product, in case it has not been used over two weeks.
2. Please use certificated charger.
3. Do not wear earphones for a long term to protect your hearing.
4. Do not wear earphones in any situations with potential risks as wearing them may reduce your perception to the outside world.

**Factory Setting**

If earphones do not function well, please refer the following steps to reset factory: take earbuds out from the case. Power off the earphones then hold MFBs on both earbuds for about 15s (LED will blink red and white three times twice). After that, put them back to the case. Delete connectivity record on cellphone before processing another pairing (All connectivity records relating to the earbuds will all be removed).

**Audio only outputs from single earbud**

It's a rare case. Please reset the earphones, remove connectivity record on your cellphone and re-connect the earphones to your cellphone.

**Other problems in charging**

LED glows solid white for 1 minute when earbuds are topped up.  
Carry case will not charge earbuds, if its battery drains. LEDs on carry case will turn off once the case is topped up. If you charge it once again, LEDs will not give any notice, which does not mean the case is not charged.

**Tips**

1. Before using the headset, please read the manual carefully and keep it for future references.
2. The headset need to be fully charged prior to first-time use.
3. If the headset is left unused for over two weeks, please recharge it periodically.
4. Please use the chargers made by qualified manufacturer.
5. If the headset cannot be found by your phone, please check whether it is in pairing mode; if left unconnected for a long while, the headset will exit pairing mode, please re-enter the mode; if a procedure error of your phone occurs, reboot it; if a procedure error of the headset occurs, reboot or reset it.

Address: Suite 1303, 1305 and 1306, 13/F, Project Phase 2 of Gaosheng Tech Tower, Gaosheng Tech Park, No.5 Longxi Road, Zhouxi Community, Nancheng District, Dongguan City, Guangdong, China.

Manufacturer: Dongguan Liesheng Electronic Co., Ltd.  
Web: www.haylou.com  
Made In China

**Hazardous substances and their contents in the item**



Part Name	Hazardous Substances									
	Pb	Hg	Cd	Cr (VI)	PBB	PBDE	DIBP	DEHP	DBP	BBP
Main body	X	O	O	O	O	O	O	O	O	O
Battery	O	O	O	O	O	O	O	O	O	O
Ear tips	O	O	O	O	O	O	O	O	O	O
Accessories	O	O	O	O	O	O	O	O	O	O
Charging cable	X	O	O	O	O	O	O	O	O	O

This form is made by SJ/T 11364 regulation.  
O: means that hazardous substance content in the homogeneous materials of this part is within the limits of (EU) 2015/863 regulation.  
X: means that hazardous substance content in, at least, one certain homogeneous material of this part is beyond the limits of (EU) 2015/863 regulation, but there is no mature alternative in the industry at present, it still conforms to the EU ROHS Directive in the scope of exemption.

Notes: Please arrange using time properly as your hearing may be damaged by using the device for a long time.

**Aftersales & Support**

Warranty Period:  
12 months after purchase  
(please keep your receipt properly)

Free Service:  
If any quality defects happen during the warranty period, please take the receipt and contact with your distributor for aftersales service.

Following cases or any damages/defects that are not due to quality issue are not covered in the warranty.

1. Any defects or damages caused by natural disasters, abnormal voltage or other environmental facts.
2. Any unauthorized disassembly, modification or change of parts.
3. Any damages caused by improper use of the product including soaking, corroding, falling down, squeezing or exposure to abnormal temperature or humidity.

Model Number:
Date of Purchasing:
User's Name:
User's Phone:
User's Address:
Shop's Name:
Shop's Address:
Comments: